

## CIRCUIT BREAKER DATA

Luminaire Family:	<b>CONCAVA</b>
Sub-families:	-
Applicable Model Range:	<b>EL-CON-1100-244</b> <b>EL-CON-1101-244</b> <b>EL-CON-1102-244</b> <b>EL-CON-1103-244</b>

Inrush Current and Maximum Loading of Automatic Circuit Breakers (MCB):										
Circuit Breaker Type	C10	C13	C16	C20	B10	B13	B16	B20	Inrush Current	
Wire cross section	1.5mm <sup>2</sup>	1.5mm <sup>2</sup>	2.5mm <sup>2</sup>	2.5mm <sup>2</sup>	1.5mm <sup>2</sup>	1.5mm <sup>2</sup>	2.5mm <sup>2</sup>	2.5mm <sup>2</sup>	I <sub>max</sub>	Time (*)
Max # of Fittings per MCB	31	43	53	66	19	26	32	40	26A	151µs

(\*): Defined as the duration between 10% of peak (ascending) and 50% of peak (descending).

Luminaire Family:	<b>CONCAVA</b>
Sub-families:	-
Applicable Model Range:	<b>EL-CON-1500-244</b> <b>EL-CON-1501-244</b> <b>EL-CON-1502-244</b> <b>EL-CON-1503-244</b>

Inrush Current and Maximum Loading of Automatic Circuit Breakers (MCB):										
Circuit Breaker Type	C10	C13	C16	C20	B10	B13	B16	B20	Inrush Current	
Wire cross section	1.5mm <sup>2</sup>	1.5mm <sup>2</sup>	2.5mm <sup>2</sup>	2.5mm <sup>2</sup>	1.5mm <sup>2</sup>	1.5mm <sup>2</sup>	2.5mm <sup>2</sup>	2.5mm <sup>2</sup>	I <sub>max</sub>	Time (*)
Max # of Fittings per MCB	21	28	36	45	13	17	22	27	22.4A	176µs

(\*): Defined as the duration between 10% of peak (ascending) and 50% of peak (descending).

### IMPORTANT:

- The above are maximum quantities calculated based on the inrush current and provided as a guide only.
- DO NOT exceed the maximum rated continuous current of the circuit breaker.
- Calculation uses typical values from ABB series S200 as a reference.
- Information about the tripping characteristics of a specific circuit breaker must be requested from the circuit breaker manufacturer!
- Actual values may differ depending on the specific circuit breaker type(s) used and the installation environment such as the cable size, length, safety buffer, etc.