

OMNIPOD

INSTALLATION INSTRUCTIONS

SPECIFICATION



Luminaire's light distribution is direct.

LED

Denotes which light source/light sources that can be supplied with the luminaire. Several symbols next to the same luminaire indicate that the luminaire is available in different designs.

IP40

IP CLASSIFICATION

IP40: Protected against solid objects over 1mm (tools, wires and small wires).



CLASS I

Appliances with functioning insulation. Equipped with an earth termination.



RISK OF FIRE

Building Insulation must not cover this Luminaire
HCB =100mm. MIC =100mm. SCB =100mm. SCI =100mm.



RCM

Indicates a device's compliance with applicable ACMA technical standards.



ESD

Personnel should be grounded when unpacking or handling the luminaire.

IMPORTANT INFORMATION

Please read this guide carefully before installing or maintaining this equipment.

Data should be used as an **INDICATION** only.

Good electrical practices should be followed at all times.

Must only be installed by a licensed electrician.

If the external flexible cable or cord of this luminaire is damaged, it shall be exclusively replaced by the manufacturer or their service agent or a similar qualified person in order to avoid a hazard.

A qualified electrician, in accordance with AS/NZS 3000:2018 wiring regulations should carry out connection to mains wiring.

This unit must be **EARTHED**.

Ensure that the rated voltage and frequency requirements are compatible with the available mains supply, 220-240V 50Hz.

Cleaning of reflectors and lenses should be carried out using clean, soft and lint free cloths and anti-static cleaning fluid.

Do not carry out high voltage insulation test i.e. 500/1000V this may damage the fixtures electrical components.

CODE INS-OMN

OMNIPOD

INSTALLATION INSTRUCTIONS

EXPOSED T-BAR

- Step 1
Lift the luminaire into the ceiling cavity.
- Step 2
Complete the electrical connection.
- Step 3
Position the luminaire centrally within the T-Bar.

PLASTER CEILING

- Step 1
Cut out the correct hole size in the ceiling for your plaster frame accessory.
- Step 2
Lift the plaster frame to the plaster cut out.
- Step 3
Fold over the retaining tabs located in the ends of the frame to assist in securing the frame.
- Step 4
Fasten the recessing brackets to the secure the frame within the ceiling cavity.
- Step 5
Lift the luminaire into the ceiling cavity.
- Step 6
Complete the electrical connection.
- Step 7
Position the luminaire centrally within the Plaster Frame.

SURFACE MOUNTED

- Step 1
Lift the surface mounted body to the ceiling, feeding the supply cable through the cable entry hole.
- Step 2
Secure the body onto the mounting surface with appropriate fasteners (not supplied) to suit the mounting substrate.
- Step 3
Complete electrical connection.
- Step 4
Slide the luminaire into the surface mounted body and connect the earth lanyard to the end.
- Step 4
Slide the end into the surface mounted body.

CODE INS-OMN