

## CIRCUIT BREAKER DATA

Luminaire Family:	<b>OPERATING THEATRE IP65L</b>
Sub-families:	<b>OPERATING THEATRE IP65L CRI95+</b>
Applicable Model Range:	<b>EL-OPSL-1261-0xx, EL-OPSL-1262-0xx, EL-OPSL-1263-0xx, EL-OPSL-1264-0xx, EL-OPSL-1265-0xx, EL-OPSL-1266-0xx, EL-OPSL-1267-0xx, EL-OPSL-1268-0xx, EL-OPSL-1269-0xx, EL-OPSL-1270-0xx, EL-OPSL-1271-0xx, EL-OPSL-1272-0xx, EL-OPSL-1273-0xx, EL-OPSL-1274-0xx.</b>

### Inrush Current and Maximum Loading of Automatic Circuit Breakers (MCB):

Automatic circuit breaker type	C10	C13	C16	C20	B10	B13	B16	B20	Inrush current	
Installation Ø	1.5 mm <sup>2</sup>	1.5 mm <sup>2</sup>	2.5 mm <sup>2</sup>	2.5 mm <sup>2</sup>	1.5 mm <sup>2</sup>	1.5 mm <sup>2</sup>	2.5 mm <sup>2</sup>	2.5 mm <sup>2</sup>	$I_{max}$	time
<b>Max # of Fittings per MCB</b>	16	21	26	35	10	13	16	21	30 A	253 µs

These are max. values calculated out of inrush current! Please consider not to exceed the maximum rated continuous current of the circuit breaker. Calculation uses typical values from ABB series S200 as a reference. Actual values may differ due to used circuit breaker types and installation environment.

### IMPORTANT:

- The above are maximum quantities calculated based on the inrush current and provided as a guide only.
- DO NOT exceed the maximum rated continuous current of the circuit breaker.
- Information about the tripping characteristics of a specific circuit breaker must be requested from the circuit breaker manufacturer!
- Actual values may differ depending on the specific circuit breaker type(s) used and the installation environment such as the cable size, length, safety buffer, etc.

Luminaire Family:	<b>OPERATING THEATRE IP65L</b>
Sub-families:	<b>OPERATING THEATRE IP65L CRI95+</b>
Applicable Model Range:	<b>EL-OPSL-1261-2xx/-9xx, EL-OPSL-1262-2xx/-9xx, EL-OPSL-1263-2xx/-9xx, EL-OPSL-1264-2xx/-9xx, EL-OPSL-1265-2xx/-9xx, EL-OPSL-1266-2xx/-9xx, EL-OPSL-1267-2xx/-9xx, EL-OPSL-1268-2xx/-9xx, EL-OPSL-1269-2xx/-9xx, EL-OPSL-1270-2xx/-9xx, EL-OPSL-1271-2xx/-9xx, EL-OPSL-1272-2xx/-9xx, EL-OPSL-1273-2xx/-9xx, EL-OPSL-1274-2xx/-9xx.</b>

**Inrush Current and Maximum Loading of Automatic Circuit Breakers (MCB):**

Automatic circuit breaker type	C10	C13	C16	C20	B10	B13	B16	B20	Inrush current	
Installation Ø	1.5 mm <sup>2</sup>	1.5 mm <sup>2</sup>	2.5 mm <sup>2</sup>	2.5 mm <sup>2</sup>	1.5 mm <sup>2</sup>	1.5 mm <sup>2</sup>	2.5 mm <sup>2</sup>	2.5 mm <sup>2</sup>	I <sub>max</sub>	time
<b>Max # of Fittings per MCB</b>	21	28	35	45	13	17	21	27	23 A	174 µs

These are max. values calculated out of inrush current! Please consider not to exceed the maximum rated continuous current of the circuit breaker.

Calculation uses typical values from ABB series S200 as a reference.

Actual values may differ due to used circuit breaker types and installation environment.

**IMPORTANT:**

- The above are maximum quantities calculated based on the inrush current and provided as a guide only.
- DO NOT exceed the maximum rated continuous current of the circuit breaker.
- Information about the tripping characteristics of a specific circuit breaker must be requested from the circuit breaker manufacturer!
- Actual values may differ depending on the specific circuit breaker type(s) used and the installation environment such as the cable size, length, safety buffer, etc.